


■ SERIES 3300 WATT PORTABLE GENERATOR

GENERAC®



FEATURING



Portable power whenever you need it. The Generac GP3300i inverter features advanced PowerRush™ technology, delivering over 50% more starting capacity for your RV essentials and other motor-driven equipment -so you can do more with less! This innovative engine design provides quiet inverter power -perfect for outdoor applications in a compact and lightweight solution



Compact and lightweight, with a built-in handle

Integrates start/run/stop functions into one easy-to-use dial

Over 50% more starting capacity

Innovative engine design reduces sound emissions and increases fuel efficiency



RUSH™



FEATURING

DOUBLE YOUR POWER PARALLEL KIT (#7668-0)

A Generac parallel kit allows you to double your power when pairing two inverter generators together with the same output.† Parallel kit sold separately.

**Increases electrical current upon demand; above rated output when starting electric motors.*

†Connect any two Generac 3300 or 3500 Series' inverters for twice the power. Applies when pairing two inverter generators with the same output. Parallel kit sold separately.



CONTROL PANEL



GENERATOR STATUS LIGHTS

Ready, overload and low oil

USB OUTLETS

Charge mobile devices including smartphones and tablets

PARALLEL READY

Connect two inverters together for twice the power (parallel kit sold separately)

Sizing a portable generator is easy. Check out this sample:

Choose which devices you want to power at the same time.

Record the running watts listed for each device. If your device only lists amps, multiply the amps by 120V to get the wattage. Ex. 15A x 120V = 1800 Watts.

Add the running watts together for all devices. This is the minimum running wattage requirement for your needs.

DEVICE	RUNNING WATTS
RV Air Conditioner (13,500 BTU) [†]	1250
LED/LCD Television	120
Blue Ray Player	15
Slow Cooker	250
Cell Phone Charger	10
RV Microwave	600
Total	2245

Minimum running Watts for your needs

↓

[†]Motor load, demands higher Watts at start-up.

Watts listed are approximate. Check your appliance for actual requirements. Total wattage requirements assumes intermittent starting of devices.

	DEVICE	RUNNING WATTS
RECREATION	RV Air Conditioner (13,500 BTU) [†]	1250
	Cell Phone Charger	10
	Box Fan - 20"	100
	Tablet	20
	Blue Ray Player	15
	LED/LCD Television	120
	Slow Cooker	250
	Laptop Computer	75
	Coffee Maker	900
	RV Microwave	600
	Blender	1000
	Hair Dryer	1500
	Lithium Ion Battery Charger	360
	Air Compressor [†]	1000
HOUSEHOLD	Circular Saw [†]	1400
	Hand Drill [†]	600
	Belt Sander [†]	1200
	Reciprocating Saw [†]	1440
	Table Saw [†]	1800
	Airless Paint Sprayer	1080
	Wet Dry Vac	900
	Quartz Halogen Work Light	1000
	Refrigerator/Freezer [†]	700
	Lights	600
	Desktop Computer	400
	Sump Pump [†]	2100
	Toaster	1200
	Window AC (12,000 BTU) [†]	3250

GP SERIES

WATT PORTABLE GENERATOR

SPECIFICATIONS	
Model #	GP3300i CO: G0071531 GP3300i CO/CSA: G0071530
Configuration	50ST/CSA
COsense	Yes
Running Watts	2500
Starting Watts	3300
Engine Type	Generac OHV
Engine Displacement	149cc
Starting Method	Recoil Pull Start
Low Oil Shutdown	Yes
Fuel Tank Capacity (Gallons)	1.06
Run Time @ 50% Load	4.5 hours
Run Time @ 25% Load	7 hours
Rated Voltage	120V
Low Total Harmonic Distortion (THD)	Less than 3%
Outlets	(2) 120V 20A 5-20R Duplex, (1) 120V 30A L5-30R Twist Lock, (2) USB Outlets
Parallel Ready	Yes
Handle Style	Single, Molded Into Enclosure
Dimensions (L" x W" x H")	22.3" x 13.4" x 18.4"
Product Weight	59.5 lbs
Warranty - Residential	3 Year Limited
Warranty - Commercial	2 Year Limited

SPECIFICATIONS	
Model # (Configuration)	7668-0
Receptacle Type	(1) 120V 50A 14-50R, (1) 120V 30A TT-30R (RV)
Covered Outlets	Yes
Rated 120 VAC Amperage	20.83 Amp
AC Rated Voltage	120V
Warranty - Residential	90 Day Limited
Warranty - Commercial	90 Day Limited
Dimensions (L" x W" x H")	9.84" x 4.33" x 8.27"

All portable specifications and models subject to change. Please consult factory for availability.

A TRADITION OF QUALITY AND INNOVATION

For over 50 years, Generac Power Systems has been a leader in innovative design and superior manufacturing. When it comes to developing products that are both durable and reliable, we stand head and shoulders above our competition. The result of our efforts can be seen across our many product offerings.

We design and build engine-driven power generation equipment, automatic transfer switches, control systems, air-cooled engines, power washers and water pumps.

Regardless of the product, our vertical integration allows us to control the quality, availability and flow of materials throughout the manufacturing process. And each product is factory tested prior to shipment. It is this ongoing commitment to quality and innovation that has made Generac a name that people have come to trust.

GENERAC®